



MMX-44UFX

8-channel audio mixer

8-channel audio mixer with 12 input,
DSP effect unit and USB interface.
Plug and mix!

- Integrated USB audio interface (will be identified and addressed as an external sound card)
- Full duplex USB port (allows for simultaneous recording and reproduction) for the reproduction of digital audio data from a PC and for recording mixings onto a PC
- 4 mono input channels, each with gain control, 3-way equalizer, low cut and pan pot
- 4 stereo input channels, each with balance control
- DSP with 100 different effects
- Aux send output
- Control room function
- Tape record/play connections
- +48 V phantom power, can be switched centrally
- Adjustable headphone output
- Stereo LED level display
- Power supply via supplied PSU

Technical data:

- Mic, mono 0.5 mV, bal.
- Line, mono 1 mV
- Line, stereo 10 mV, bal.
- Insert, mono -
- Tape, stereo 100 mV
- Aux, stereo 100 mV
- Master, stereo L/R 650 mV
- Control room, stereo 2 V
- Record, stereo 650 mV
- Insert, mono -
- Aux1, mono 9.5 V
- Aux2, mono -
- Headphones, stereo = 8 Ω
- Frequency range 20-20,000 Hz
- THD < 0.05 %
- S/N ratio > 74 dB
- Crosstalk -63 dB
- Bass ±15 dB/80 Hz
- Mid range ±15 dB/2.5 kHz
- Treble ±15 dB/12 kHz
- Phantom power +48 V
- Power supply via suppl. PSU
- Admissible ambient temp. 0-40 °C
- Dimensions (WxDxH) 280x50x260 mm
- Weight 2.5 kg



For complete manual, please refer to univox.eu.

