



MMX-602/SW

Microphone line mixer

Features

- Microphone line mixer, 6 channels.
- 6 stereo line inputs, 6 balanced mono microphone inputs, switchable
- Adjustable automatic talkover (-12 dB), switchable for channel 1 or channels 1+2
- Balance control for each stereo input channel
- 3-way equalizer
- 12 V phantom power can be switched on additionally
- LED VU meter, peak LED
- Master output and record output
- Output can be switched stereo/mono
- Adjustable headphone output
- 482 mm (19") rack installation, 1 RS

Microphone line mixer with 6 line inputs and adjustable automatic talkover.

Art.nr: 600600



Copyright © Bo Edin AB

TECHNICAL DATA:

Line input, stereo	100 mV/10 k Ω
Microphone input	1 mV/6.6 k Ω
Master output, stereo	1 V/600 Ω
Record output, stereo	310 mV/600 Ω
Headphones, stereo	> 8 Ω
Frequency range	20-20,000 Hz
THD	0.1 %
S/N ratio	62 dB, unweighted
Equalizer, bass	\pm 12 dB/50 Hz
Equalizer, midrange	\pm 12 dB/1 kHz
Equalizer, treble	\pm 12 dB/10 kHz
Power supply	230 V~/50 Hz/12 VA
Admiss. ambient temp.	0-40 $^{\circ}$ C
Dimensions	482x47x208 mm, 1 RS
Weight	2.8 kg
Line input, stereo	6 x RCA L/R
Microphone input	6 x XLR, bal.
Master output, stereo	1 x RCA L/R, 1 x XLR L/R, bal.
Record output, stereo	1 x RCA L/R
Headphones	1 x 6.3 mm jack

