



# Univox® IRR-1

## Pendant Infrared Receiver

### Features

- IR transparent case for wider scope of coverage and greater sensitivity
- Li-Polymer battery for quick charging and light weight
- Selectable 2.3 and 2.8 MHz carrier frequencies
- 2 mono channels or 1 stereo
- Unit automatically turns on when 3.5 mm jack is inserted
- USB charging port (cable included)
- Lanyard (included) and pocket spring clip on back to wear in a variety of ways
- Slide volume and channel selection for simple operation
- Designed to be used with either Univox neck loop or head-/earphones (accessories)



### High Performing Assistive Listening

Univox® IRR-1 receiver is a wireless 2-channel, stereo infrared pendant receiver designed for professional applications. Equipped with multiple receiving diodes for increased sensitivity, the receiver works with transmitters operating on 2.3/2.8 MHz bandwidth.

Powered by a rechargeable Lithium Polymer battery, this lightweight receiver is to be worn around the neck, pendant-style (with supplied lanyard) or clipped on a pocket. The unit is easy to operate – select the channel frequency and adjust the volume with the intuitive slide volume control.

Univox® IRR-1 receiver can be used with Univox NL-90 neck induction loop to supplement personal hearing aids with a telecoil /T-switch setting, as well as with EM-101 single-sided earphone and EM-201 headphones for users with no or little hearing loss.

### Univox IR System



Transmitter IR 1411  
Receiver IRR-1  
USB 5 slot charger station

# Univox® IRR-1 IR Receiver

## Technical data

|                                  |   |
|----------------------------------|---|
| <b>Modulation</b>                | FM, 1kHz $\pm$ 75kHz  |
| <b>IR Light Wavelength</b>       | 850nm   |
| <b>Carrier Frequency</b>         | 2.3MHz, 2.8MHz<br>or Stereo: 2.3MHz (Left) and 2.8MHz (Right) |
| <b>Audio Frequency response</b>  | 100Hz-10kHz, -3dB to +2dB                                     |
| <b>Total Harmonic Distortion</b> | <1%   |
| <b>Signal-to-noise Ratio</b>     | <55dB   |
| <b>Battery</b>                   | 3.7V Lithium Polymer 500mAh                                   |
| <b>Operation time</b>            | Approx. 8 hours   |
| <b>Charging time</b>             | <4 hours  |
| <b>Power Connection</b>          | USB (micro-USB to USB)  |
| <b>Indicators</b>                | Green LED: power on<br>Red LED: charging                      |
| <b>Output</b>                    | 3.5mm   |
| <b>Weight</b>                    | 58g incl battery  |
| <b>Size</b>                      | (W) 45 x (D) 12 x (H) 82mm                                    |
| <b>Color</b>                     | Black   |
| <b>Part no</b>                   | 650301  |

## Accessories

|        |   |
|--------|---|
| 283101 | NL-90 Neck loop, 3.5mm plug, black, cable 55cm    |
| 230903 | EM-201 Headphones, 3.5mm stereo, cable 1.2m       |
| 230904 | Headphone pad, spare part for EM-201              |
| 581407 | EM-101 Earphone, on-ear, 3.5mm stereo, cable 90cm |



NL-90 Neckloop



EM-201 Headphones



EM-101 Earphone



Univox IRR-1 IR receiver

For complete manual, please refer to [univox.eu](http://univox.eu).

